

# 5 Zone Mixer Amplifier with USB/SD/FM/Blue Tooth EA-60Z/EA-120Z/EA-240Z/EA-350Z/EA-500Z/EA-650Z



## Features:

- Tabletop 5 zone mixer amplifier with Mp3 player, FM radio & blue tooth
- Rate power output at 60W, 120W, 240W, 350W, 500W & 650W
- 5 zone speaker outputs 100V & single zone speaker output of 100V or 70V & 4 Ohm-8 Ohm-16 Ohm
- Mp3 player with USB/SD input on front panel, IR remote control for Mp3 player, FM radio and blue tooth
- EXT Chime for closed trigger input to activate the 4 tone chime and siren
- Mic1 priority & mute level attenuator
- Phantom power for Mic1 & Mic 2
- 7 Inputs includes Mic1-5 XLR inputs and Aux 1-2 inputs
- Amp input and Pre output for external amplifier link
- EQ of low, middle, high and master tone control
- Complete amplifier protection includes short-circuit, clip, overload and high temp

## Specification:

Model	EA-60Z	EA-120Z	EA-240Z	EA-350Z	EA-500Z	EA-650Z
Description	5 Zone Mixer Amplifier with USB/SD/FM/Blue Tooth					
Rated Power Output	60W	120W	240W	350W	500W	650W
Speaker Outputs	100V or 70V & 4 Ohm-8 Ohm-16 Ohm 5 Zone speaker outputs 100V					
Connector	Mic1-5 input by balanced XLR; Aux 1 RCA input, Aux 2 6.3mm phone jack input Amp input 6.3mm phone jack, Pre Output 6.3mm phone jack EXT Chime for closed trigger input to activate the 4 tone chime and siren Mic1 Mute attenuator, Mic1-2 +48V phantom power on/off dipswitch					
Input	MIC1-5: 5-8mV, 600 Ω ; Aux 1-2, 150-470mV, 10K Ω					
Line Out	0.775(0dBV)					
Frequency Response	60Hz-15kHz(±3dB)					
S/N Ratio	Line ≥ 85dB, Mic ≥ 72dB					
THD	Less than 0.5%					
Protection	Short-circuit, clip, overload and high temp protection					
Power Consumption	80W	150W	310W	450W	650W	800W
Power Supply	AC230V; 50-60Hz					
Dimension	484×350×88mm					
Weight	7.0kg	7.1kg	8.6kg	8.7kg	8.9kg	9.2kg

## Rear Panel:

