

DA-21000/DA-21500/DA-22000

Two Channel PA Power Amplifier



Features:

- Switching power technology digital power amplifier
- Two channel PA power amplifier of minimum power consumption
- 1RU height for less rack space and less heat generation
- Dual channel power amplifier into 19" rack mount unit
- Rated power output at 2 x 1000W, 2 x 1500W & 2 x 2000W
- Speaker outputs 4-16Ω/100V
- Two channel balanced line input by XLR & Link out
- With volume control on front panel
- Separate indicators for power, signal & clip
- Complete protection includes short circuit, overload, high temp & clip

Description:

The DA-21000 range two channel power amplifier is of switching power technology, which features of minimum power consumption and much higher efficiency up to 85%, moreover it helps to save installation rack space, generate less heat so as to extend its performance life span. The DA-21000 range two channel power amplifiers are of rated power output at 2 x 1000W, 2 x 1500W & 2 x 2000W, so it could be used as 2 zone digital public address system at minimum cost. The versatile loudspeaker outputs of both high impedance 100V & low impedance 4-16 Ohms enable it meet both PA fixed installation and Hi-fi stereo sound installation jobs. There are two balanced inputs by phoenix connector with volume control on front panel. Visual working status indicators include power, signal & clip for easy amplifier working status monitoring. With complete protection includes short circuit, overload, high temp and clip etc.

Specification:

Model	DA-21000	DA-21500	DA-22000
Description	Class-D PA Power Amplifier		
Rated Power Output	2 x 1000W	2 x 1500W	2 x 2000W
Speaker Output	4-16 Ω & 100V		
Frequency Response	40Hz-16KHz		
Input	1V, 1.2KΩ(Bal)/600Ω(balanced)		
Input Impedance	10KΩ		
THD	<0.3%		
S/N Ratio	>90dB		
Power Consumption	2600W	3600W	5000W
Power Supply	AC 220V-240V, 50-60Hz		
Dimension	484x375x44mm		
Weight	8kg	10.5kg	12.5kg

Rear Panel:

