

2 Zone Mixer Amplifier with USB/SD/FM/Blue Tooth EA-30T/EA-60T/EA-120T



Feature:

- Compact 2 zone public address amplifier
- Tabletop 2 zone mixer amplifier with Mp3 player, FM radio & blue tooth
- Rate power output at 30W, 60W to 120W
- Speaker output of 100V or 70V & 4 Ohm-8 Ohm-16 Ohm
- 2 zone speaker outputs of 100V with separate zone attenuator
- Mp3 player with USB/SD input on front panel, IR remote control for Mp3 player, FM radio and blue tooth
- LED indicators for power, clip, protect and signal
- Mic1 of balanced XLR input with dipswitch of phantom power on/off & highest VOX priority on/off
- Mic/line 2-3 switchable input unbalanced 6.3mm jack
- Line 1-2 input of RCA input and one RCA line output
- Telephone input with secondary priority and MOH (Music on Hold)
- Volume control for Mic1-3, line1-2, TEL, bass/treble and master
- Complete amplifier protection includes short-circuit, clip, overload and high temp
- 230V AC & 24V DC both power supply system
- Optional to add DAB & DAB+ module

Specification:

Model	EA-30T	EA-60T	EA-120T
Description	2 Zone Mixer Amplifier with USB/SD/FM/Blue Tooth		
Rated Power Output	30W	60W	120W
Speaker Outputs	100V or 70V & 4 Ohm-8 Ohm-16 Ohm Two Zone speaker outputs of 100V with separate zone attenuator		
Connector	Mic1 input by balanced XLR with phantom power & VOX highest priority Mic/line switchable input 2-3 unbalanced 6.3mm jack Telephone input with secondary priority and MOH (Music on Hold) Line1-2 inputs by RCA; Line output by RCA		
Input	MIC1-3: 5-8mV, 600Ω; Line, 150-470mV, 10KΩ, unbalanced RCA		
Line Out	0.775(0dBV)		
Frequency Response	60Hz-15kHz(±3dB)		
S/N Ratio	Line ≥ 85dB, Mic ≥ 72dB		
THD	Less than 0.5%		
Protection	Short-circuit, clip, overload and high temp protection		
Power Consumption	60W	100W	200W
Power Supply	230V AC & 24V DC; 50-60Hz		
Dimension	320×210×90mm		
Weight	3.7kg	4.2kg	4.8kg

Rear Panel:

