



Features:

- Bluetooth wireless connectivity
- Built-in stereo amplifier of 2 x 15 watts output
- Internal Bluetooth, USB/SD media player and FM tuner
- Supplied with I.R. remote control
- Volume control through panel keys or the supplied remote control
- 5 program of timer to scheduled power on/off
- 30 levels of attenuation through remote control or key functions on front panel
- Memory setting, with contact for door bell and remote trigger broadcast
- Black or white color option

Description:

A3 In-Wall Amplifier with Bluetooth/USB/FM with 2 x 15W digital stereo amplifiers built into a single gang wall plate. Powered directly from 100-240V mains supply, the wall mount amplifier can be installed into a partition wall or 57mm back box and provides a minimal yet fully functional control surface. The on wall amplifier has an inbuilt USB/Micro SD audio player, an FM tuner and Bluetooth receiver. Key functions are operated from the front panel or by using the supplied IR remote control. Connections for 2 low impedance speakers, mains power, FM antenna and up to 2 external line inputs are provided at the rear on screw terminal phoenix connectors. A complete and versatile audio solution for wall or ceiling background music speakers in the home or commercial audio applications

Specification:

| | |
|--------------------|---|
| Model | A3 |
| Description | In-Wall Amplifier with Bluetooth/USB/FM |
| Power Supply | 100-240V AC, 50/60Hz (screw terminal) |
| Rated Power Output | 2x15W@ 8 Ohms |
| Audio Format | mp3, wma, wav, flac, ape, dts, aac, ac3, ogg |
| Video Format | Mpeg-1/2/3/4, rm/rmvp, wmv, mov, mk, vob, avi, 3gp, h.264 |
| FM Range | 87.5-108mHz |
| Distance | IR remote control & Bluetooth distance up 20 meters |
| Frequency Response | 20Hz~20KHz (at±0.3dB) |
| THD | <0.03% at 1kHz, 1W |
| SN Ratio | >98dB |
| Volume | Bass: ±15dB; Treble: ±15dB |
| Dimension | 86 x 86 x 50mm |
| Mounting | 86 x 86 x 57mm |
| Color | Black or white |
| Weight | 128g |