

PA-100MP

8 Zone Weekly Timer with USB/FM



Features:

- Public address system intelligent controller.
- Ideal PA sound system controller for school, shopping mall, hotel, and intelligent office etc.
- All in one intelligent PA system controller built in weekly timer, 8 zone speaker selector, Mp3 player & FM, fire alarm and voice evacuation system interface, monitor and programmable power sequencer.
- One amplifier or 4 amp inputs divided into 8 zones speaker output.
- Built-in 5W hi-fi monitor speaker with volume control.
- With one microphone input, one line input, one USB input and one EMC input and two line outputs
- Auto timely broadcast up to 99 program sources.
- Broadcast modes: random, repeat and circle.
- 4 regular programs and 1 spare program for emergency/particular circumstance.
- Functional swift key for internal MP3 player priority manual broadcast.
- Flash memory capacity support 4GB and 8GB.
- Audio source format support Mp3/MAV and WMA
- The system communication distance up to 1kms
- Memory function even in case of power off.

Specification:

Model	PA-400U
Description	PA System Weekly Timer with Mp3 & FM
Amplifier Input	1 or 4 Amplifier inputs
Zone Output	8 zone speaker outputs, 100V or 70V
Mic1. Input	5~8mV , 600ohms(Ω),unbalanced
Line1 Input	300mV , 10k ohms(Ω),unbalanced
Line1-2 Output	500mV 10k ohms(Ω),unbalanced
Memory Capacity	4GB
Program AC Power Outputs	4 outputs
Monitor Speaker	Full range speaker 5w, 8ohms, hi-fi
S/N Ratio	>90dB
Frequency Response	20Hz~ 18KHz
Power Supply	AC220V or 115V, 50-60Hz
Power Consumption	15~20W
Dimension	88×484×350mm
Net Weight	6.42kg

Rear Panel:

